

## Wizord 4i

The Wizord energizers have been field tested for many years and boast unsurpassed reliability. Simple to install and easy to maintain.

## **Features**

- 3.7 Joule output energy (single zone)
- Robust and flexible design for home and commercial security
- Built-in alarm monitors tampering or faults on the high voltage and earth fence wires
- Connectable to armed response radio or GSM module
- Lightning and power surge protection
- Intelligent power saving to extend battery life
- Easy-to-use tag included for controlling the energizer
- Powered by 240V mains and includes built-in battery for back-up power
- Built-in gate alarm input to monitor if the gate is open or closed



Enclosure size: L285 x W212 x D120 Weight excluding battery (7AH): 3.1kg Weight including battery (7AH): 5.3kg

IP rating: IPx4

Operating temperatures: -10°C to 50°C Operating humidity: < 80% non-condensing

Electrical supply voltage: 240V

Typical power consumption (normal operating conditions): 18VA

Standby time (fully charged battery): 24hrs Energy output 500 Ohms load: 3.7 Joule

Open circuit voltage: 8 000V



Stock Code	Name	Description
E-WIZ4I	Wizord 4i	Wizord 4i - 4J Energizer
E-WIZ4I/EU	Wizord 4i	Wizord 4i - 4J Energizer - EU Plug
E-WIZ4I/UK	Wizord 4i	Wizord 4i - 4J Energizer - UK Plug

